

AZEEZ FIYINFOLUWA ANDREW

15/ENG04/012

ELECTRICAL ELECTRONICS ENGINEERING

1. $D = 1500m$

Schedule Speed = $36km/hr = 36 \times \frac{5}{18} = 10m/s$

Breaking Retardation $\beta = 3 \times \frac{5}{18} = \frac{5}{6} m/s^2$

$t = \frac{d}{v} \therefore t = \frac{d}{v} = 1500/10 = 150s$

Actual runtime = $150 - 25 = 125s$

$$V_a = \frac{1500}{125} = 12m/s$$

$$V_{max} = 1.25 \times 12 = 15m/s$$

$$k = \frac{D}{V_m^2} \left[\frac{V_m}{V_a} - 1 \right] = \frac{1500}{15^2} (1.25 - 1)$$

$$= \frac{5}{3}$$

$$\text{Recall } k = \frac{1}{2} \left(\frac{1}{\alpha} + \frac{1}{\beta} \right)$$

$$\frac{5}{3} = \frac{1}{2} \left(\frac{1}{\alpha} + \frac{6}{5} \right)$$

$$\alpha = 0.4 m/s^2 = 0.41 \times \frac{18}{5}$$

$$= 1.7 km/h/s$$

\therefore acceleration $\alpha = 1.7 km/h/s$

2. $V_a = 36km/h = 36 \times \frac{5}{18} = 10m/s$

$\alpha = 1.8 m/h/s = 1.8 \times \frac{5}{18} = 0.5 m/s^2$

$\beta = 3.6 km/h/s = 3.6 \times \frac{5}{18} = 1.0 m/s^2$

$t = \frac{2000}{10} = 200s$

$$k = \frac{(\alpha + \beta)}{2\alpha\beta} = \frac{(0.5 + 1.0)}{2(0.5 \times 1)} = 1.5$$

$$V_m = \frac{t - \sqrt{t^2 - 4kD}}{2k} = \frac{200 - \sqrt{200^2 - 4 \times 1.5 \times 2000}}{2 \times 1.5}$$

$$= 11m/s = 11 \times \frac{18}{5}$$

$$= 39.6 km/h$$

3. Total Surface area of tank = $6l^2$

$$\therefore 6l^2 = 6, \quad l = \frac{6}{6} = 1\text{m}^2$$

Total volume of tank = $l^3 = 1\text{m}^3$

Volume of water to be heated daily = $6 \times (1 \times 0.9) = 5.4\text{m}^3$

Since 1m^3 of water = 1000kg

Mass of water = $5.4 \times 1000 = 5400\text{kg}$

Heat required to raise temperature of water = $5400 \times 4200 \times (65-20)$
 $= 1020\text{mt}$

If $1\text{kWh} = 3.6\text{mt}$

Then $1020\text{mt} = 1020/3.6$

$$= 283.3\text{kWh}$$

Daily loss from the tank = $6.3 \times 6 \times (65-20) \times 24 / 1000$
 $= 40.8\text{kWh}$

Energy supplied per day = $283.3 + 40.8 = 324.1\text{kWh}$

Loading in kWh = $324.1/24$

$$= 3.5\text{kW}$$

Efficiency of the tank = $\frac{283.3}{324.1} \times 100$

$$= 87.4\%$$

4. Secondary Current = $\frac{600 \times 10^3}{20 \times 0.6} = 5 \times 10^4 \text{A}$

If this current is taken as the reference quantity,

$$V_2 = 20(0.6 + j0.8) = (12 + j16)\text{V}$$

$$\therefore \text{Secondary Impedance } Z_2 = \frac{(12 + j16)}{(5 \times 10^4)}$$

$$= (2.4 + j3.2) \times 10^{-4} \text{ohms}(\Omega)$$

$$\therefore Z_2 = (4.8 + j3.2) \times 10^{-4} \Omega$$

$$\text{Second Current } I_2 = \frac{20}{(4.8 \times 13.7) \times 10^{-4}}$$

$$= 3.466 \angle -33.7^\circ \times 10^4 \text{ A}$$

$$\text{Pf} = \cos 33.7 = 0.832$$

$$\therefore \text{Power absorbed} = 20 \times 3.466 \times 10^4 \times 0.832 \times 10^4 \\ = 580 \text{ kW}$$

5) No reflector

$$\text{a) } \theta = \frac{300}{20^2}$$

$$= 0.75 \text{ lm/m}^2$$

$$\text{b) } \theta = \tan^{-1} \left(\frac{10}{20} \right) = \tan^{-1} (0.5) = 26.6^\circ$$

$$\cos \theta = 0.89, r^2 = 10^2 + 20^2 = 500$$

$$\therefore \theta = \frac{300}{0.89 \times 500}$$

$$= 0.534 \text{ lm/m}^2$$

with reflector

$$\text{luminous output of the lamp} = 300 \times 4 \pi \text{ lumen}$$

$$\text{Flux directed by the reflector} = 0.5 \times 1200 \pi \\ = 600 \pi$$

$$\text{illuminator produced on disc} = \frac{600 \pi}{100 \pi}$$

$$= 6 \text{ lm/m}^2$$

\therefore Same with energy point on the disc.