

ODOGWU PETER CHINEDU
15/ENG Oct/040

EEE 552 ASSIGNMENT
9i) Recall $R = \frac{E}{L} = \frac{I}{r^2}$

Therefore,

$$L = \frac{E}{R}$$

Considering reflection factor,

$$L = \left(\frac{E}{R} \right) \times \text{reflection factor}$$

$$L = \frac{44,000}{\pi} \times \frac{85}{100}$$

$$L = 11.905 \times 10^3 \text{ cd/m}^2 \text{ or } 1.19 \times 10^4 \text{ cd/m}^2$$

$$\text{ii) } L = \frac{0.22}{\pi} \times \frac{85}{100}$$

$$L = 59.52 \times 10^{-3} \text{ cd/m}^2$$

bi) Flux emitted by source

$$\Phi = I \times \omega = 120 \times 4\pi = 480\pi \text{ lumens}$$

Flux emitted by globe (30% is absorbed)

$$480\pi \times \frac{30}{100} = 144\pi \text{ lumens}$$

$$\therefore \text{Flux emitted by globe} = 480\pi - 144\pi = 336\pi \text{ lumens}$$

$$\text{Luminance} = \frac{\text{Flux emitted}}{A \times r^2} = \frac{336\pi}{\pi \times 0.22^2} = 6942 \text{ lm/m}^2$$

$$\begin{aligned}
 \text{ii) Card power (CP)} &= \frac{\text{Lumen}}{W} \\
 &= \frac{336 \pi}{4 \pi} \\
 &= \underline{\underline{84 \text{ cd}}}
 \end{aligned}$$

$$\begin{aligned}
 \text{c) } A &= 75 \times 10^{-4} \text{ m}^2 \approx 75 \text{ cm}^2 \\
 t &= 2 \times 10^{-2} \text{ m} \approx 2 \text{ cm}
 \end{aligned}$$

$$\text{Heat required} = mc \Delta \theta$$

$$\text{Density} = \frac{m}{V}$$

$$[\text{Recall } V = A \times t]$$

$$m = \text{Density} \times V$$

$$m = 0.55 \frac{\text{g}}{\text{cm}^3} \times (75 \times 2) \text{ cm}^3$$

$$m = 82.5 \text{ g}$$

$$C = \frac{\epsilon_0 \epsilon_r A}{t} = \frac{8.85 \times 10^{-12} \times 6.5 \times 75 \times 10^{-4}}{2 \times 10^{-2}}$$

$$C = 21.57 \times 10^{-12} \text{ F}$$

$$\omega = 2\pi f = 2\pi \times 20 \times 10^6 = 125.664 \times 10^6 \text{ rad/s}$$

$$\text{power factor} = \cos \phi = 0.04$$

$$\phi = \cos^{-1}(0.04) = 87.7^\circ$$

$$\delta = 90 - \phi = 90 - 87.7 = 2.3^\circ$$

$$\text{Heat required} = mc \Delta \theta$$

$$= 82.5 \times 0.255 \times (80 - 30)$$

$$= 1051.88 \text{ cal}$$

$$\text{Total heat required} = 1051.88 \times \frac{85}{100} = 894.098 \text{ cal}$$

$$1 \text{ cal} = 4.186 \text{ (W}\cdot\text{s)} \bar{\delta}$$

$$894.098 \text{ cal} = x$$

$$\text{Power}^x \text{ input} = 894.098 \times 4.186 = 3742.7 \text{ (W}\cdot\text{s)}$$

$$P = \frac{\text{Energy}}{\text{Time}} = \frac{3742.7}{8 \times 60} = 7.797 \text{ W}$$

$$P_d = V^2 \omega C \tan \delta$$

$$7.797 = V^2 \times 125.664 \times 10^6 \times 21.57 \times 10^{-12} \times \tan 2.3^\circ$$

$$V^2 = \frac{7.797}{1.08868 \times 10^{-4}}$$

$$V = \underline{\underline{267.62 \text{ V}}}$$

$$P = IV \cos \phi$$

$$I = \frac{7.797}{267.62 \times 0.04}$$

$$I = \underline{\underline{0.7284 \text{ A}}}$$