

$$\textcircled{2} \quad \varnothing_{\text{inlet}} = 300\text{mm} = 0.3\text{m} \quad A = \frac{\pi d^2}{4} = 0.07\text{m}^2$$

$$\varnothing_{\text{throat}} = 150\text{mm} = 0.15\text{m} \quad A = \frac{\pi d^2}{4} = 0.0177\text{m}^2$$

$$s \cdot \rho_m = 13.6$$

$$s_1 = 0.9, \quad z_1 - z_2 = 300\text{mm} = 0.3\text{m}$$

$$y = 250\text{mm} = 0.25\text{m}, \quad \omega = \rho_g = 8.829$$

$$h = \left[ \frac{P_1}{\omega} - \frac{P_2}{\omega} \right] + (z_1 - z_2) = y \times \left[ \frac{s_2}{s_1} - 1 \right]$$

$$h = 0.25 \left[ \frac{13.6}{0.9} - 1 \right] = 3.53\text{m}$$

$$i \quad Q = c_d \cdot A_1 A_2 \times \sqrt{2gh}$$

$$\sqrt{A_1^2 - A_2^2}$$

$$= 0.98 \times \frac{0.07 \times 0.0177}{\sqrt{0.07^2 - 0.0177^2}} \times \sqrt{2 \times 9.81 \times 3.53}$$

$$= \underline{0.1489\text{m}^3/\text{s}}$$

$$ii \quad \frac{P_1 - P_2}{\omega} = h + (z_1 - z_2)$$

$$\frac{P_1 - P_2}{\omega} = 3.53 + 0.3$$

$$\frac{P_1 - P_2}{\omega} = 3.83$$

$$P_1 - P_2 = 3.83 \times \omega = \underline{33.8 \times 10^3 \text{N/m}^2}$$

Kazie Nnenna

Mechatronics

18/ENG051026

①  $s.g = 0.8$

$\varnothing_{inlet} = 150\text{mm} = 0.15\text{m}$      $A = \frac{\pi d^2}{4} = 0.0177\text{m}^2$

$\varnothing_{throat} = 75\text{mm} = 0.075\text{m}$      $A = \frac{\pi d^2}{4} = 0.0044\text{m}^2$

$z_2 - z_1 = 150\text{mm} = 0.15\text{m}$

$Q = 40\text{lit/sec} = 0.04\text{m}^3/\text{s}$

$c_d = 0.96$ ,  $\omega = \rho g = 7848$

$$Q = \frac{c_d \cdot A_1 \cdot A_2}{\sqrt{A_1^2 - A_2^2}} \times \sqrt{2gh}$$

$$0.04 = 0.96 \times \frac{0.0177 \times 0.0044}{\sqrt{0.0177^2 - 0.0044^2}} \times \sqrt{2 \times 9.81 \times h}$$

$$h = \frac{0.04}{(0.96 \times 0.00457 \times 4.429)^2}$$

$$= 4.247\text{m}$$

$$h = \left[ \frac{P_1}{\omega} - \frac{P_2}{\omega} \right] + (z_1 - z_2)$$

$$4.247 = \frac{P_1 - P_2}{\omega} + 0.15$$

$$P_1 - P_2 = 7848 \times (0.15 + 4.247)$$

$$= \underline{34.51 \times 10^3 \text{ N/m}^2}$$