


Adanoh Yusuf


171EN002/003

COMPUTER ENGINEERING



J K Truth table

| J | K | Q |
|---|---|-----------|
| 0 | 0 | No change |
| 0 | 1 | Reset (0) |
| 1 | 0 | Set (1) |
| 1 | 1 | Toggle |



Timing diagram showing frequency division

BINARY COUNTING

SYSTEM

| 2^4 | 2^3 | 2^2 | 2^1 | 2^0 |
|-------------------------|-------------------------|-------------------------|-------------------------|--------------------------------|
| <u>Q_3</u> | <u>Q_2</u> | <u>Q_1</u> | <u>Q_0</u> | |
| 0 | 0 | 0 | 0 | 0 |
| 0 | 0 | 0 | 1 | After pulse 1 |
| 0 | 0 | 1 | 0 | After pulse 2 |
| 0 | 0 | 1 | 1 | After pulse 3 |
| 0 | 1 | 0 | 0 | After pulse 4 |
| 0 | 1 | 0 | 1 | After pulse 5 |
| 0 | 1 | 1 | 0 | After pulse 6 |
| 0 | 1 | 1 | 1 | After pulse 7 |
| 1 | 0 | 0 | 0 | After pulse 8 |
| 1 | 0 | 0 | 1 | After pulse 9 |
| 1 | 0 | 1 | 0 | After pulse 10 |
| 1 | 0 | 1 | 1 | After pulse 11 |
| 1 | 1 | 0 | 0 | After pulse 12 |
| 1 | 1 | 0 | 1 | After pulse 13 |
| 1 | 1 | 1 | 0 | After pulse 14 |
| 1 | 1 | 1 | 1 | After pulse 15 |
| 0 | 0 | 0 | 0 | After pulse 16 (returns to 00) |
| 0 | 0 | 0 | 1 | After pulse 17 |
| 0 | 0 | 1 | 0 | After pulse 18 |
| 0 | 0 | 1 | 1 | After pulse 19 |

2) i) MOD number = $2^6 = 64$

ii) Frequency of the 6th flip flop will equal the input clock frequency divided by MOD number
 \Rightarrow frequency of $2 \frac{1}{16} \text{ MHz} = 156.25 \text{ Hz}$


iii) The counter will count from 000000 to 111111
(a total of 64 states)

iv) Since it is a MOD-64 counter, every 64 pulses will bring the counter back to its initial state. Therefore, after 128 pulses, the counter is back to 000000 and after the 129th pulse, it brings the counter to 000001 state.

A3 - BIT ASYNCRONOUS COUNTER

- Block Diagram

High



CLK_0



Q_0

Primary
Output

Q_1

| State | Q_2 | Q_1 | Q_0 |
|-------|-------|-------|-------|
| 0 | 0 | 0 | 0 |
| 1 | 0 | 0 | 1 |
| 2 | 0 | 1 | 0 |
| 3 | 0 | 1 | 1 |
| 4 | 1 | 0 | 0 |
| 5 | 1 | 0 | 1 |
| 6 | 1 | 1 | 0 |
| 7 | 1 | 1 | 1 |

Truth
Table